

KENWOOD

L-1000D


MODEL

SERVICE MANUAL


- (X32-1722-70)
- IC1 : μ PC7805HF
 IC2-6,10 : NJM4558D-A
 IC7 : CXA1081S
 IC8 : μ PD4053BC
 IC9 : CXA1244S
 IC11 : CXD1165Q
 IC12 : M5218P
 IC13 : TC74HCU04AP
 IC14 : TC74HC74AP
 IC16 : CX20197
- Q1,3,61,63,66~68,70,73 : 2SB941
 Q2,22 : 2SC945(A)(Q,P) or 2SC1740S(Q,R)
 Q10,12,19,26 : 2SC3940A
 Q11,13,20,21 : 2SA1534A
 Q18 : DTC124EN
 Q50 : 2SA733(A)(Q,P) or 2SA933S(Q,R)
 Q60,62,64,65,69,71,72 : 2SD1266
 Q162 : 2SK118
 D1-5,7,9-12 : S5566B
 D6 : RD8.2ES(B2) or HZS8.2N(B2)
 D8 : RD30ES(B) or HZS30N(B)
 D13,15 : RD5.1JS(B2) or HZS5.1S(B2)
 D16,17,19,20,24,25,47~49 : ISS133 or HSS104
 D18 : ISV147
 D14 : RD3.9HS
 D71 : RBV1402LFA

— SIGNAL LINE
 — GND LINE
 — +B LINE
 - - - -B LINE

MECHA. ASS'Y CDM-07(C)
 (X92-1320-02)



(X32-1722-70) (A/5)



DTC124EN
 2SA1534A
 2SA733(A)
 2SC3940A

2SA933S
 2SC1740S

2SB941

2SD1266

μ PC7805HF

CX20197
 M5218P


NJM4558D-A

TC74HCU04AP
 TC74HC74AP

CXA1081S
 CXA1244S

CXD1165Q

CAUTION: For continued components only with manu (refer to part's list). Ind nents. To reduce the risk of e or resistance measurement parts are acceptably insula before the appliance is retu




! : For continued safety, replace safety critical parts only with manufacturer's recommended parts (parts list). ⚠ Indicates safety critical components. The risk of electric shock, leakage current measurements shall be carried out (exposed parts acceptably insulated from the supply circuit) appliance is returned to the customer.

• DC voltages are as measured with a high impedance voltmeter. Values may vary slightly due to variations between individual instruments or/and units.

Y22-1932-70


L-1000D
KENWOOD



- (X32-1722-70) (B/5)
- IC102~107 : NJM5532D-D
 - IC108~111 : M5238P
 - IC112, 113 : CX20152
 - IC114 : CXD1144B
 - IC115 : TC74HC86AP
 - IC116 : 74AC74PC
 - IC117 : M74HC6004P
 - IC118 : M51951ASL
 - IC119 : NJM4558L-D
 - IC120, 121 : NJM4558D-A
 - PH1 : T95-0116-05
 - PH2~4 : T95-0114-05

SIGNAL LINE
GND LINE
+B LINE
-B LINE

- 2SA733(A)
2SC2003
2SC945(A)
- 2SA1206
- DTA124ES
2SA933S
2SC1740S
- 2SK152
- 2SK170
- 2SK246
- M51951ASL
- NJM4558L-D
- M5238P
M74HC6004P
- NJM4558D-A
NJM5532D-D
- 74AC74PC
- μPD4053BC
- CXD1144B
- CX20152
- μPD75216ACW




B/5)
45532D-D
238P
20152
01144B
4HC86AP
4C74PC
4HC6004P
1951ASL
M4558L-D
M4558D-A
5-0116-05
5-0114-05

Q101~108,122
Q109,110 : 2SK152 (3,4)
Q111,153 : 2SK246 (GR)
Q113 : 2SD1509
Q115~117,152 : 2SC945(A)(Q,P) or 2SC1740S(Q,R)
Q118 : 2SA733(A)(Q,P) or 2SA933S(Q,R)
Q119,127 : 2SA1206
Q120,121 : 2SK170(V)
Q138 : 2SB1250
Q139~141 : 2SD1509
Q150 : 2SC2003(L,K)
Q165 : 2SK118

D108,115 : RD12JS(B)
D112,113,117~120,122,123,151 : RD5.1JS(B2) or HZS5.1S(B2)
D114 : RD3.9HS
D121,152 : RD7.5JS(B) or HZS7.5S(B)
D127,129~132,160 : E-102
D144 : ISS133 or HSS104
D133~136 : E-202

(X25-3720-00)
IC1 : μ PD75216ACW-A79
IC2 : M51951ASL
Q1,2 : 2SC945(A)(Q,P)
Q3,4 : DTA124ES
D1,3~9,21,28 : HSS104 or ISS133
D2 : RD6.8ES(B2) or HZS6.8N(B2)
D10~18 : B30-1283-05
D19,20 : B30-1011-05

(X32-1722-70) (C/5)
IC101 : NJM4550D-A
Q26 : 2SC3246(H,J)
Q76 : 2SB1250
Q77 : 2SD1890
Q129 : 2SK363(V)
Q132 : 2SA733(A)(Q,P) or 2SA933S(Q,R)
Q133 : 2SC945(A)(Q,P) or 2SC1740S(Q,R)
Q136 : 2SK152 (3,4)
D50 : ISS133 or HSS104
D106,107 : RD12JS(B)
D124,125 : HZS15S(B) or RD15JS(B)
D126 : RD5.1JS(B2) or HZS5.1S(B2)
D140,141,146 : E-102



CAUTION : For continued safety, replace safety critical components only with manufacturer's recommended parts (refer to parts list). Δ Indicates safety critical components. To reduce the risk of electric shock, leakage-current or resistance measurements shall be carried out (exposed parts are acceptably insulated from the supply circuit) before the appliance is returned to the customer.


• DC voltages are as measured with a high impedance voltmeter. Values may vary slightly due to variations between individual instruments or/and units.

Y22-1932-70

L-1000D
KENWOOD

L-1000D L-1000D


EXPLODED VIEW (MECHANISM)



Parts with the exploded numbers larger than 700 are not supplied.

61

EXPLODED VIEW (UNIT)



Parts with the exploded numbers larger than 700 are not supplied.

62

L-1000D

PARTS LIST

× New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕 向	Re- marks 備考
L-1000D						
603	2C	*	A20-5910-15	PANEL		
604	2C	*	A22-1142-12	SUB PANEL ASSY		
606	2C	*	A29-0155-24	PANEL ASSY (TRAY)		
609	1C, 2E	*	A50-0335-03	SIDE PLATE ASSY		
610	1C	*	A52-0141-02	TOP PLATE ASSY		
611	1C	*	A70-0315-05	REMOTE ASSY(RC-1000D)		
612	1C	*	A09-0100-08	BATTERY COVER		
615	1E	*	B09-0068-05	CAP		
616	2C	*	B10-1052-04	FRONT GLASS		
617	2C	*	B19-1502-04	LIGHTING BOARD		
-	-	*	B07-1917-04	ESCUTCHEON		
-	-	*	B46-0092-03	WARRANTY CARD	K	
-	-	*	B46-0096-13	WARRANTY CARD	X	
-	-	*	B46-0121-03	WARRANTY CARD	P	
-	-	*	B46-0122-13	WARRANTY CARD	EE1	
-	-	*	B46-0143-13	WARRANTY CARD	T	
-	-	*	B50-9904-00	INSTRUCTION MANUAL(ENGLISH)		
-	-	*	B50-9905-00	INSTRUCTION MANUAL(FRENCH)	EPE1	
-	-	*	B50-9907-00	INSTRUCTION MANUAL(GER, DUT, IT)	EE1	
-	-	*	B58-0400-04	CAUTION CARD		
-	-	*	B58-0695-04	CAUTION CARD		
618	1C	*	E30-2621-05	AUDIO CORD (BLUE)		
619	1C	*	E30-2622-05	AUDIO CORD (RED)		
△620	1E	*	E30-0459-05	AC POWER CORD	E1	
△620	1E	*	E30-0780-05	AC POWER CORD	KP	
△620	1E	*	E30-1341-05	AC POWER CORD	X	
△620	1E	*	E30-1416-05	AC POWER CORD	T	
△620	1E	*	E30-2580-05	AC POWER CORD	E	
621	1C	*	E30-2600-05	CORD WITH PLUG		
622	1C, 1D	*	E31-7442-05	WIRING HARNESS		
623	1E	*	E31-7537-25	WIRING HARNESS		
624	1D, 1C	*	E31-7648-05	WIRING HARNESS		
626	1D	*	G01-1925-04	COMPRESSION SPRING		
627	2E	*	G01-2104-04	COMPRESSION SPRING		
-	-	*	H01-8651-04	ITEM CARTON CASE		
-	-	*	H10-3907-12	POLYSTYRENE FOAMED FIXTURE		
-	-	*	H10-3908-12	POLYSTYRENE FOAMED FIXTURE		
-	-	*	H25-0232-04	PROTECTION BAG (235X350X0.03)		
-	-	*	H25-0387-14	PROTECTION BAG		
-	-	*	H25-0395-04	PROTECTION BAG		
630	1D, 1E	*	J02-0192-05	INSULATOR		
631	2E	*	J02-1055-05	FOOT		
632	1D	*	J11-0096-05	WIRE CLAMPER		
633	1D, 1E	*	J11-0163-05	WIRE CLAMPER		
634	1D, 1E	*	J19-0515-05	UNIT HOLDER		
635	1D	*	J19-3180-05	UNIT HOLDER		
636	1E	*	J21-5528-03	MOUNTING HARDWARE ASSY		
637	1D	*	J21-5529-03	MOUNTING HARDWARE ASSY		
△638	1D, 1E	*	J31-0036-04	COLLAR		
640	2E	*	J39-0154-04	SPACER		

E1: Scandinavia K: USA P: Canada E: Europe

V: PX(Far East, Hawaii) T: England M: Other Areas

Y: AAFES(Europe) X: Australia

△ indicates safety critical components

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
△ 641	1E		J41-0024-15	POWER CORD BUSHING	E	
△ 641	1E		J42-0083-05	POWER CORD BUSHING	KP	XT
△ 642	2D		J19-0586-05	UNIT HOLDER		
643	1E		J61-0033-05	WIRE BAND		
-			J61-0054-05	WIRE BAND		
-			J61-0081-05	WIRE BAND		
645	2C	*	K29-3798-04	KNØB (POWER)		
646	2C	*	K29-3799-04	KNØB (STOP/PLAY/POUSE)		
647	2D	*	K29-3800-04	KNØB (FB/FF/DOWN/UP)		
648	2C	*	K29-3801-04	KNØB (DISPLAY/OFF)		
649	2D	*	K29-3802-04	KNØB (OPEN/CLOSE)		
△ 652	1D	*	L07-0001-15	POWER TRANSFORMER (ANALOG)	EXT	E1
△ 652	1D	*	L07-0003-15	POWER TRANSFORMER (ANALOG)	KP	
△ 653	1E	*	L07-0005-05	POWER TRANSFORMER (DIGITAL)	EXT	E1
△ 653	1E	*	L07-0007-05	POWER TRANSFORMER (DIGITAL)	KP	
A	1E, 2D	*	N09-2776-05	SEMS (TAPTITE SCREW)		
C	1D		N09-1785-05	STEPPED SCREW		
D	2D, 2E		N09-2649-05	STEPPED SCREW		
E	1C, 2E		N09-2707-15	DRESSED SCREW		
F	1D, 1E	*	N14-0188-05	BUILD-IN NUT		
G	1E	*	N09-2775-05	MACHINE SCREW		
H	1D, 1E	*	N35-4014-45	BINDING HEAD MACHINE SCREW		
J	1D, 1E	*	N86-3016-46	BINDING HEAD TAPTITE SCREW		
K	2C		N88-3008-45	FLAT HEAD TAPTITE SCREW		
L	1C, 1D		N89-3008-46	BINDING HEAD TAPTITE SCREW		
N	2C		N09-0287-05	SEMS (TAPTITE SCREW)		
W	2E		N89-3014-45	BINDING HEAD TAPTITE SCREW		
POWER SUPPLY (X25-3720-00)						
D10 -18			B30-1283-05	LED		
D19 -20			B30-1011-05	LED (SLP-481C-50)		
C1			CE04KW1A101M	ELECTRØ 100UF 10WV		
C2			CF92FV1H103J	MF 0.010UF J		
C3			CE04KW1J100M	ELECTRØ 10UF 63WV		
C4			CF92FV1H103J	MF 0.010UF J		
C5			CE04KW1C330M	ELECTRØ 33UF 16WV		
C6			CF92FV1H103J	MF 0.010UF J		
C7 -8			CE04KW1A101M	ELECTRØ 100UF 10WV		
C9 -10			CE04KW1C222M	ELECTRØ 2200UF 16WV		
C11 -14			CF92FV1H103J	MF 0.010UF J		
C15 -16			CE04KW1E222M	ELECTRØ 2200UF 25WV		
C17 -18			CE04KW1A471M	ELECTRØ 470UF 10WV		
C19 -20			C90-1814-05	ELECTRØ 22UF 25WV		
C21		*	C90-1817-05	ELECTRØ 100UF 10WV		
CN1			E10-2704-05	FLAT CABLE CONNECTOR		
L1			L40-2291-17	SMALL FIXED INDUCTOR		
L3 -8			L33-0328-05	CHOKE COIL		
X1		*	L78-0271-05	RESONATOR		
L	1E, 2C		N89-3008-46	BINDING HEAD TAPTITE SCREW		
M	1E		N30-3006-46	PAN HEAD MACHINE SCREW		
Y	1E		N29-0265-05	PUSH RIVET		
R27 -28			RN14BK2C4641F	RN 4.64K F 1/6W		

E: Scandinavia K: USA P: Canada E: Europe

Y: PX (Far East, Hawaii) T: England M: Other Areas

Y: AAFES (Europe) X: Australia

△ indicates safety critical components.

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
R29		*	RN14BK2C5111F	RN 5.11K F 1/6W		
R30			RN14BK2C4641F	RN 4.64K F 1/6W		
R31			RN14BK2C3161F	RN 3.16K F 1/6W		
R32			RN14BK2C4641F	RN 4.64K F 1/6W		
R33 -34			RS14KB3D680J	FL-PROOF RS 68 J 2W		
S1 -9			S40-1064-05	PUSH SWITCH		
A1			W02-0975-05	ELECTRIC CIRCUIT MODULE		
D1			HSS104	DIODE		
D1			ISS133	DIODE		
D2			HZS6.8N(B2)	ZENER DIODE		
D2			RD6.8ES(B2)	ZENER DIODE		
D3 -9			HSS104	DIODE		
D3 -9			ISS133	DIODE		
D21			HSS104	DIODE		
D21			ISS133	DIODE		
D28			HSS104	DIODE		
D28			ISS133	DIODE		
D30 -31			IC4841	DIODE		
D32 -34			E-102	CONSTANT CURRENT DIODE		
D35 -36			RD10JS(B2)	ZENER DIODE		
D37			RD5.1JS(B2)	ZENER DIODE		
FL1		*	FIP98FM8	FLUORESCENT INDICATOR TUBE		
IC1			UPD75216ACW-A79	IC (MICROPROCESSOR)		
IC2			M51951ASL	IC (SYSTEM RESET)		
IC4			NJM4558D	IC (OP AMP X2)		
Q1 -2			2SC945(A)(Q,P)	TRANSISTOR		
Q3 -4			DTA124ES	DIGITAL TRANSISTOR		
Q5			2SC945(A)(Q,P)	TRANSISTOR		
Q6			2SA733(A)(Q,P)	TRANSISTOR		
Q6			2SA933S(Q,R)	TRANSISTOR		
Q7			2SB1250	TRANSISTOR		
Q8			2SD1890	TRANSISTOR		
CONTROL (X32-1722-70)						
△ C1 -3			C91-0971-05	FILM 0.01UF 250WV		
C4			CF92FV1H103J	MF 0.010UF J		
C5			CE04KW1E221M	ELECTRØ 220UF 25WV		
C6			CF92FV1H104J	MF 0.10UF J		
C7			CE04KW1A471M	ELECTRØ 470UF 10WV		
C8 -11			CF92FV1H103J	MF 0.010UF J		
C12			CE04KW1H101M	ELECTRØ 100UF 50WV		
C13			CF92FV1H103J	MF 0.010UF J		
C14 -15			CE04KW1C682M	ELECTRØ 6800UF 16WV		
C16 -17			CE04KW1C101M	ELECTRØ 100UF 16WV		
C18 -19			CE04KW1E330M	ELECTRØ 33UF 25WV		
C20 -21			CE04KW1A471M	ELECTRØ 470UF 10WV		
C22			CF92FV1H102J	MF 1000PF J		
C23			CF92FV1H152J	MF 1500PF J		
C24			CF92FV1H121K	MF 120PF K		
C25			CF92FV1H222J	MF 2200PF J		
C26			CF92FV1H103J	MF 0.010UF J		
C27			C90-1331-05	NP-ELEC 0.47UF 50WV		
C28			CF92FV1H103J	MF 0.010UF J		
C30			CF92FV1H103J	MF 0.010UF J		

E: Scandinavia K: USA P: Canada E: Europe

Y: PX (Far East, Hawaii) T: England M: Other Areas

Y: AAFES (Europe) X: Australia

△ indicates safety critical components.

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
C32			CE04KW1H010M	ELECTR 1.0UF 50WV		
C41			CE04KW1E101M	ELECTR 100UF 25WV		
C42			CE04KW1E330M	ELECTR 33UF 25WV		
C43			CF92FV1H333J	MF 0.033UF J		
C44, 45			C91-0168-05	POLYSTY 15PF K		
C46			CE04KW1E330M	ELECTR 33UF 25WV		
C47			CF92FV1H333J	MF 0.033UF J		
C48			CF92FV1H103J	MF 0.010UF J		
C49			CE04KW1E330M	ELECTR 33UF 25WV		
C50			C91-0171-05	POLYSTY 27PF K		
C51			CF92FV1H332J	MF 3300PF J		
C52			CF92FV1H474J	MF 0.47UF J		
C53			CF92FV1H103J	MF 0.010UF J		
C54			C91-0171-05	POLYSTY 27PF K		
C55, 56			CE04KW1E330M	ELECTR 33UF 25WV		
C57			C90-1350-05	NP-ELEC 2.2UF 50WV		
C58			CF92FV1H104J	MF 0.10UF J		
C59			CF92FV1H121K	MF 120PF K		
C60			CE04KW1V100M	ELECTR 10UF 35WV		
C61			CF92FV1H121K	MF 120PF K		
C62			C90-1350-05	NP-ELEC 2.2UF 50WV		
C63, 64			CF92FV1H822J	MF 8200PF J		
C65			C90-1455-05	NP-ELEC 0.1UF 50WV		
C66			CF92FV1H103J	MF 0.010UF J		
C67			C91-0174-05	POLYSTY 47PF K		
C68, 69			CE04KW1A471M	ELECTR 470UF 10WV		
C70			CF92FV1H821J	MF 820PF J		
C71			CF92FV1H104J	MF 0.10UF J		
C72			C90-1351-05	NP-ELEC 3.3UF 50WV		
C73			CF92FV1H124J	MF 0.12UF J		
C74			CF92FV1H102J	MF 1000PF J		
C75			C90-1350-05	NP-ELEC 2.2UF 50WV		
C76			CE04KW1A101M	ELECTR 100UF 10WV		
C77			CF92FV1H102J	MF 1000PF J		
C79, 80			CF92FV1H103J	MF 0.010UF J		
C81, 82			CE04KW1A471M	ELECTR 470UF 10WV		
C83			CF92FV1H124J	MF 0.12UF J		
C84			CF92FV1H101K	MF 100PF K		
C85, 86			CF92FV1H222J	MF 2200PF J		
C87			CC45FUJ1H050C	CERAMIC 5.0PF C		
C88			CC45FUJ1H101J	CERAMIC 100PF J		
C89			CC45FUJ1H330J	CERAMIC 33PF J		
C90, 91			CF92FV1H103J	MF 0.010UF J		
C92			CF92FV1H222J	MF 2200PF J		
C94, 95			CE04KW1E330M	ELECTR 33UF 25WV		
C101			CE04KW0J102M	ELECTR 1000UF 6.3WV		
C127		*	CQ93HP2A102F	MYLAR 1000PF F		
C141			CE04KW1E221M	ELECTR 220UF 25WV		
C195, 196			CF92FV1H102J	MF 1000PF J		
C200-203			CF92FV1H102J	MF 1000PF J		
C204-207			C90-1807-05	ELECTR 100UF 25WV		
C210, 211		*	CQ93HP2A183F	MYLAR 0.018UF F		
C212, 213		*	CF92FV1H071J	MF 770PF J		
C214, 215		*	CQ93HP2A153F	MYLAR 0.015UF F		
C216		*	CQ93HP2A102F	MYLAR 1000PF F		

E1: Scandinavia K: USA P: Canada E: Europe

Y: PX(Far East, Hawaii) T: England M: Other Areas

Y: AAFES(Europe) X: Australia

A indicates safety critical components

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
C218, 219		*	CQ93HP2A562F	MYLAR 5600PF F		
C220, 221		*	CQ93HP2A152F	MYLAR 1500PF F		
C222, 223		*	CQ93HP2A332F	MYLAR 3300PF F		
C224		*	CF92FV1H391J	MF 390PF J		
C226, 227		*	CF92FV1H391J	MF 390PF J		
C228-231		*	CQ93HP2A152F	MYLAR 1500PF F		
C232-235			CF92FV1H122J	MF 1200PF J		
C236			CE04KW1V222M	ELECTR 2200UF 35WV		
C238			CE04KW1V222M	ELECTR 2200UF 35WV		
C240, 241		*	C90-1820-05	ELECTR 470UF 25WV		
C242		*	C90-1817-05	ELECTR 100UF 10WV		
C243, 244			C90-1814-05	ELECTR 22UF 25WV		
C246, 247			CF92FV1H221J	MF 220PF J		
C255		*	CF92FV1H391J	MF 390PF J		
C304			CF92FV1H221J	MF 220PF J		
C306, 307			C90-1807-05	ELECTR 100UF 25WV		
C308			C90-1814-05	ELECTR 22UF 25WV		
C309		*	C90-1817-05	ELECTR 100UF 10WV		
C311, 312			C90-1807-05	ELECTR 100UF 25WV		
C313, 314			CE04KW1A101M	ELECTR 100UF 10WV		
C315, 316		*	C90-1814-05	ELECTR 22UF 25WV		
C317			C90-1817-05	ELECTR 100UF 10WV		
C318			CE04KW1A471M	ELECTR 470UF 10WV		
C319			CE04KW1E101M	ELECTR 100UF 25WV		
C320, 321			C90-1814-05	ELECTR 22UF 25WV		
C323			CE04KW1A471M	ELECTR 470UF 10WV		
C324			CF92FV1H102J	MF 1000PF J		
C326			C91-0757-05	CERAMIC 1000PF K		
C327			CE04KW1A471M	ELECTR 470UF 10WV		
C328-330			CE04KW1A101M	ELECTR 100UF 10WV		
C331			CF92FV1H103J	MF 0.010UF J		
C334-337			CE04KW1A101M	ELECTR 100UF 10WV		
C338, 339			C90-1807-05	ELECTR 100UF 25WV		
C340		*	C90-1817-05	ELECTR 100UF 10WV		
C342, 343			CE04KW1V102M	ELECTR 1000UF 35WV		
C344, 345			CF92FV1H102J	MF 1000PF J		
C346			C91-0166-05	POLYSTY 10PF D		
C347			C91-0162-05	POLYSTY 6PF F		
C349		*	C90-1817-05	ELECTR 100UF 10WV		
C359, 360			CF92FV1H222J	MF 2200PF J		
C361			CF92FV1H103J	MF 0.010UF J		
C365-367			CE04KW1E331M	ELECTR 330UF 25WV		
C401, 402			CE04KW1E101M	ELECTR 100UF 25WV		
C403		*	C90-1817-05	ELECTR 100UF 10WV		
C404, 405			CE04KW1E101M	ELECTR 100UF 25WV		
C406		*	C90-1817-05	ELECTR 100UF 10WV		
C407, 408			CE04KW1E101M	ELECTR 100UF 25WV		
C409			CF92FV1H102J	MF 1000PF J		
C410, 411			CE04KW1A471M	ELECTR 470UF 10WV		
C412			CF92FV1H103J	MF 0.010UF J		
C413			CE04KW1A471M	ELECTR 470UF 10WV		
C415			CE04KW1A101M	ELECTR 100UF 10WV		
C416, 417			CE04KW1E101M	ELECTR 100UF 25WV		
C418			CE04KW1E221M	ELECTR 220UF 25WV		
C501, 502			CE04KW1E330M	ELECTR 33UF 25WV		

E1: Scandinavia K: USA P: Canada E: Europe

Y: PX(Far East, Hawaii) T: England M: Other Areas

Y: AAFES(Europe) X: Australia

A indicates safety critical components

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
C503, 504 C505 C506-508 C509 C510-512			CF92FV1H103J CF92FV1H223J CF92FV1H103J CF92FV1H221J CE04KW1E330M	MF 0.010UF J MF 0.022UF J MF 0.010UF J MF 220PF J ELECTRO 33UF 25WV		
C513-515 C516 C517, 518 C519 C520			CF92FV1H103J CF92FV1H102J CE04KW1C331H CE04KW1E330M CE04KW1A101M	MF 0.010UF J MF 1000PF J ELECTRO 330UF 16WV ELECTRO 33UF 25WV ELECTRO 100UF 10WV		
CN15 J500 J600 J700 J800	1D 1E 1E 1E	*	E10-2703-05 E13-0137-05 E13-2202-05 E06-0306-05 E06-0306-05	FLAT CABLE CONNECTOR PHONE JACK (COAXIAL) PHONE JACK (2P) CYLINDRICAL RECEPTACLE (3P) CYLINDRICAL RECEPTACLE (3P)		
△656 △656 △L1 L2 -7 L8 ,9	1D 1D		L01-7651-05 L01-7652-05 L79-0733-05 L33-0328-05 L40-1021-14	POWER TRANSFORMER POWER TRANSFORMER LINE FILTER CHOKE COIL SMALL FIXED INDUCTOR(1.0MH,K)	XP EXTE1	
L10 L11 ,12 L13 L14 L16			L40-1001-17 L40-1021-14 L40-1021-11 L40-1021-14 L92-0026-05	SMALL FIXED INDUCTOR(10UH,K) SMALL FIXED INDUCTOR(1.0MH,K) SMALL FIXED INDUCTOR SMALL FIXED INDUCTOR(1.0MH,K) CORE		
L17 L18 L19 ,20 L21 L105			L40-1011-17 L39-0152-05 L40-2291-17 L32-0328-15 L40-1011-17	SMALL FIXED INDUCTOR(100UH,K) MATCHING COIL SMALL FIXED INDUCTOR OSCILLATING COIL SMALL FIXED INDUCTOR(100UH,K)		
L106,107 L108,109 L110 L111 L112,113		*	L40-1021-14 L40-1011-17 L40-1091-17 L39-0197-05 L40-1011-17	SMALL FIXED INDUCTOR(1.0MH,K) SMALL FIXED INDUCTOR(100UH,K) SMALL FIXED INDUCTOR MATCHING COIL SMALL FIXED INDUCTOR(100UH,K)		
X1 L M			L77-1128-05 N89-3008-46 N30-3006-46	CRYSTAL RESONATOR BINDING HEAD TAPTITE SCREW PAN HEAD MACHINE SCREW		
R12 R13 R16 ,17 R18 ,19 R45		*	RN14BK2C2611F RN14BK2C1002F RN14BK2C4751F RN14BK2C1001F RN14BK2C3162F	RN 2.61K F 1/6W RN 10.0K F 1/6W RN 4.75K F 1/6W RN 1.00K F 1/6W RN 31.6K F 1/6W		
R114 R119 R146,147 R149 R198-203		*	RS14KB3D6R8J RS14KB3D6R8J RN14BK2E27R0F RN14BK2E27R0F RN14BK2E10R0F	FL-PROOF RS 6.8 J 2W FL-PROOF RS 6.8 J 2W RN 27.0 F 1/4W RN 27.0 F 1/4W RN 10.0 F 1/4W		
R208-211 R214-217 R220,221 R222,223 R224,225		*	RN14BK2E1003F RN14BK2E1002F RN14BK2C1004F RN14BK2E8200F RN14BK2E1961F	RN 100K F 1/4W RN 10.0K F 1/4W RN 1.00M F 1/6W RN 820.0 F 1/4W RN 1.96K F 1/4W		

E1: Scandinavia K: USA P: Canada E: Europe

Y: PX(Far East, Hawaii) T: England M: Other Areas

Y: AAFES(Europe) X: Australia

△ indicates safety critical components.

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
R226-237 R238, 239 R240-245 R246-249 R250, 251		*	RN14BK2E2211F RN14BK2C2211F RN14BK2E2211F RN14BK2E3921F RN14BK2E2211F	RN 2.21K F 1/4W RN 2.21K F 1/6W RN 2.21K F 1/4W RN 3.92K F 1/4W RN 2.21K F 1/4W		
R252-259 R300-302 R303 R304 R306		*	RN14BK2C2211F RN14BK2C4751F RN14BK2C6811F RN14BK2C4641F RN14BK2C6811F	RN 2.21K F 1/6W RN 4.75K F 1/6W RN 6.81K F 1/6W RN 4.64K F 1/6W RN 6.81K F 1/6W		
R307 R311 R312 R313, 314 R316, 317		*	RN14BK2C4751F RN14BK2C2611F RN14BK2C1002F RN14BK2C4751F RN14BK2C4751F	RN 4.75K F 1/6W RN 2.61K F 1/6W RN 10.0K F 1/6W RN 4.75K F 1/6W RN 4.75K F 1/6W		
R318 R319 R320 R321 R325			RN14BK2C1002F RN14BK2C2611F RN14BK2C1002F RN14BK2C2611F RN14BK2C1003F	RN 10.0K F 1/6W RN 2.61K F 1/6W RN 10.0K F 1/6W RN 2.61K F 1/6W RN 100K F 1/6W		
R326-328 R329-331 R332 R333 R334		*	RN14BK2C1000F RN14BK2C3320F RN14BK2C4751F RN14BK2C3321F RN14BK2C4751F	RN 100.0 F 1/6W RN 332.0 F 1/6W RN 4.75K F 1/6W RN 3.32K F 1/6W RN 4.75K F 1/6W		
R335 R336 R337 R341-343 R345-347		*	RN14BK2C3321F RN14BK2C4751F RN14BK2C3321F RN14BK2C1000F RN14BK2C1000F	RN 3.32K F 1/6W RN 4.75K F 1/6W RN 3.32K F 1/6W RN 100.0 F 1/6W RN 100.0 F 1/6W		
R348, 349 R350, 351 R352-355 R356-359 R364		*	RN14BK2C4751F RN14BK2C8251F RN14BK2C1211F RN14BK2C4221F RN14BK2C22R0F	RN 4.75K F 1/6W RN 8.25K F 1/6W RN 1.21K F 1/6W RN 4.22K F 1/6W RN 22.0 F 1/6W		
R366 R368 R370 R379 R400			RN14BK2C1000F RN14BK2C2211F RN14BK2C2211F RN14BK2C4641F RN14BK2C1003F	RN 100.0 F 1/6W RN 2.21K F 1/6W RN 2.21K F 1/6W RN 4.64K F 1/6W RN 100K F 1/6W		
R401 R501 R517 R518 VR1		*	RN14BK2C1000F RN14BK2C75R0F RN14BK2C1002F RN14BK2E27R0F R12-3128-05	RN 100.0 F 1/6W RN 75.0 F 1/6W RN 10.0K F 1/6W RN 27.0 F 1/4W TRIMMING POT. (22K) TE BAL		
VR2 -4 VR5 VR6 ,7		*	R12-3126-05 R12-0118-05 R12-2046-05	TRIMMING POT. (10K) FE BAL/GAIN TRIMMING POT. (470) LRCK TRIMMING POT. (1K) I-SET		
△K1 K2 -4 S1	1D 1D		S51-1052-05 S51-2074-05 S31-2094-05	MAGNETIC RELAY MAGNETIC RELAY SLIDE SWITCH		
PH1 PH2 -4		*	T95-0116-05 T95-0114-05	OPTO ISOLATOR OPTO ISOLATOR		

E1: Scandinavia K: USA P: Canada E: Europe

Y: PX(Far East, Hawaii) T: England M: Other Areas

Y: AAFES(Europe) X: Australia

△ indicates safety critical components.

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
D1 -5			S5566B	DIODE		
D6			HZS8.2N(B2)	ZENER DIODE		
D6			RD8.2ES(B2)	ZENER DIODE		
D7			S5566B	DIODE		
D8			HZS30N(B)	ZENER DIODE		
D8			RD30ES(B)	ZENER DIODE		
D9 -12			S5566B	DIODE		
D13			HZS5.1S(B2)	ZENER DIODE		
D13			RD5.1JS(B2)	ZENER DIODE		
D14		*	RD3.9HS	ZENER DIODE		
D15			HZS5.1S(B2)	ZENER DIODE		
D15			RD5.1JS(B2)	ZENER DIODE		
D16 ,17			HSS104	DIODE		
D16 ,17			1SS133	DIODE		
D18			1SV147	VARISTOR		
D19 ,20			HSS104	DIODE		
D19 ,20			1SS133	DIODE		
D24 ,25			HSS104	DIODE		
D24 ,25			1SS133	DIODE		
D47 -50			HSS104	DIODE		
D47 -50			1SS133	DIODE		
D71			RBV1402LFA	DIODE		
D106-108			RD12JS(B)	ZENER DIODE		
D112,113			HZS5.1S(B2)	ZENER DIODE		
D112,113			RD5.1JS(B2)	ZENER DIODE		
D114		*	RD3.9HS	ZENER DIODE		
D115			RD12JS(B)	ZENER DIODE		
D117-120			HZS5.1S(B2)	ZENER DIODE		
D117-120			RD5.1JS(B2)	ZENER DIODE		
D121			HZS7.5S(B)	ZENER DIODE		
D121			RD7.5JS(B)	ZENER DIODE		
D122,123			HZS5.1S(B2)	ZENER DIODE		
D122,123			RD5.1JS(B2)	ZENER DIODE		
D124,125			HZS15S(B)	ZENER DIODE		
D124,125			RD15JS(B)	ZENER DIODE		
D126			HZS5.1S(B2)	ZENER DIODE		
D126			RD5.1JS(B2)	ZENER DIODE		
D127			E-102	CONSTANT CURRENT DIODE		
D129-132			E-102	CONSTANT CURRENT DIODE		
D133-136			E-202	CONSTANT CURRENT DIODE		
D140,141			E-102	CONSTANT CURRENT DIODE		
D144			HSS104	DIODE		
D144			1SS133	DIODE		
D146			E-102	CONSTANT CURRENT DIODE		
D151			HZS5.1S(B2)	ZENER DIODE		
D151			RD5.1JS(B2)	ZENER DIODE		
D152			HZS7.5S(B)	ZENER DIODE		
D152			RD7.5JS(B)	ZENER DIODE		
D160			E-102	CONSTANT CURRENT DIODE		
D170			S5566B	DIODE		
IC1			UPC7805HF	IC(VOLTAGE REGULATOR/ +5V)		
IC2 -6			NJM4558D-A	IC(OP AMP X2)		
IC7			CXA1081S	IC(RF AMP)		
IC8			UPD4053BC	IC(3-INPUT ZCH MPX/DE-MPX)		
IC9			CXA1244S	IC(SERV0 SIGNAL PROCESSOR)		

E1: Scandinavia K: USA P: Canada E: Europe

Y: PX(Far East, Hawaii) T: England M: Other Areas

V: AAFES(Europe) X: Australia

⚠ indicates safety critical components

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
IC10			NJM4558D-A	IC(OP AMP X2)		
IC11			CXD1165Q	IC(DIGITAL SIGNAL PROCESSOR)		
IC12			M5218P	IC(OP AMP X2)		
IC13			TC74HC004AP	IC(CMOS INVERTER)		
IC14			TC74HC74AP	IC(DUAL D-TYPE FLIP FLOP)		
IC16			CX20197	IC(OP AMP X2)		
IC101			NJM4558D-A	IC(OP AMP X2)		
IC102-107			NJM5532D-D	IC(OP AMP X2)		
IC108-111			M5238P	IC(OP AMP)		
IC112, 113			CX20152	IC(16-BIT D/A CONVERTER)		
IC114		*	CXD1144B	IC(DIGITAL FILTER)		
IC115			TC74HC86AP	IC		
IC116			74AC74PC	IC(D-FLIP FLOP)		
IC117		*	M74HC6004P	IC(TRIPLE UNBUFFERED INVERTER)		
IC118			M51951ASL	IC(SYSTEM RESET)		
IC119			NJM4558L-D	IC(OP AMP X2)		
IC120, 121			NJM4558D-A	IC(OP AMP X2)		
Q1			2SB941	TRANSISTOR		
Q2			2SC1740S(Q,R)	TRANSISTOR		
Q2			2SC945(A)(Q,P)	TRANSISTOR		
Q3			2SB941	TRANSISTOR		
Q10			2SC3940A	TRANSISTOR		
Q11			2SA1534A	TRANSISTOR		
Q12			2SC3940A	TRANSISTOR		
Q13			2SA1534A	TRANSISTOR		
Q18			DTC124EN	DIGITAL TRANSISTOR		
Q19			2SC3940A	TRANSISTOR		
Q20 ,21			2SA1534A	TRANSISTOR		
Q22			2SC1740S(Q,R)	TRANSISTOR		
Q22			2SC945(A)(Q,P)	TRANSISTOR		
Q26			2SC3246(H,J)	TRANSISTOR		
Q50			2SA733(A)(Q,P)	TRANSISTOR		
Q50			2SA933S(Q,R)	TRANSISTOR		
Q60			2SD1266	TRANSISTOR		
Q61			2SB941	TRANSISTOR		
Q62			2SD1266	TRANSISTOR		
Q63			2SB941	TRANSISTOR		
Q64 ,65			2SD1266	TRANSISTOR		
Q66 -68			2SB941	TRANSISTOR		
Q69			2SD1266	TRANSISTOR		
Q70			2SB941	TRANSISTOR		
Q71 ,72			2SD1266	TRANSISTOR		
Q73			2SB941	TRANSISTOR		
Q76			2SB1250	TRANSISTOR		
Q77			2SD1890	TRANSISTOR		
Q101-108			2SK152(3,4)	FET		
Q109,110			2SK170(BL,V)	FET		
Q111			2SK246(GR)	FET		
Q113			2SD1509	TRANSISTOR		
Q115-117			2SC1740S(Q,R)	TRANSISTOR		
Q115-117			2SC945(A)(Q,P)	TRANSISTOR		
Q118			2SA733(A)(Q,P)	TRANSISTOR		
Q118			2SA933S(Q,R)	TRANSISTOR		
Q119			2SA1206	TRANSISTOR		
Q120,121			2SK170(V)	FET		

E1: Scandinavia K: USA P: Canada E: Europe

Y: PX(Far East, Hawaii) T: England M: Other Areas

Y: AAFES(Europe) X: Australia

△ indicates safety critical components.

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕向	Re- marks 備考
Q122			2SK152(3,4)	FET		
Q124			2SK152(3,4)	FET		
Q127			2SA1206	TRANSISTOR		
Q129			2SK363(V)	FET		
Q132			2SA733(A)(Q,P)	TRANSISTOR		
Q132			2SA933S(Q,R)	TRANSISTOR		
Q133			2SC1740S(Q,R)	TRANSISTOR		
Q133			2SC945(A)(Q,P)	TRANSISTOR		
Q136			2SK152(3,4)	FET		
Q138			2SB1250	TRANSISTOR		
Q139-141			2SD1509	TRANSISTOR		
Q150			2SC2003(L,K)	TRANSISTOR		
Q151			2SK152(3,4)	FET		
Q152			2SC1740S(Q,R)	TRANSISTOR		
Q152			2SC945(A)(Q,P)	TRANSISTOR		
Q153			2SK246(GR)	FET		
Q162			2SK118	FET		
Q165			2SK118	FET		
A1	1E		W02-1036-05	TRANSMITTING ASSY(OPTICAL)		
MECHANISM (X92-1320-03)						
7	2A, 3B	*	B09-0201-04	CAP		
10	1B		D10-2231-04	ARM ASSY		
11	1B		D10-2233-04	ROD		
12	2A		D10-2234-03	SLIDER		
13	2B		D10-2235-13	SLIDER		
14	1A		D10-2237-13	ARM		
15	3B		D10-2238-04	ROD		
16	3B		D10-2270-04	ROD		
17	3A	*	D10-2478-04	ROD		
18	1B		D13-0725-04	GEAR		
19	1B		D13-0726-03	GEAR		
20	1B		D13-0744-04	GEAR		
21	2B		D15-0285-04	PULLEY		
22	2B		D15-0286-04	PULLEY		
23	2B		D15-0287-04	PULLEY		
24	2B		D15-0288-04	PULLEY		
25	2B		D16-0192-04	BELT		
26	1B		D19-0253-24	WIRE		
27	1B		D23-0237-04	RETAINER		
28	3B		D23-0238-05	RETAINER		
29	3B		D32-0177-04	STOPPER		
32	2B	*	E31-7255-05	WIRING HARNESS (10P) WHITE		
33	2B	*	E31-7256-05	WIRING HARNESS (11P) GREEN		
34	2B	*	E31-4624-05	WIRING HARNESS (4P) GREEN		
35	1B	*	E31-4625-15	WIRING HARNESS (4P) WHITE		
37	3B	*	F07-0568-04	COVER		
40	3B		G01-2105-04	COMPRESSION SPRING (DM)		
41	1A		G01-2281-04	EXTENSION SPRING		
42	2A	*	G01-2472-04	COMPRESSION SPRING		
43	3B	*	G01-2473-04	COMPRESSION SPRING		
44	1A, 1B	*	G11-1302-04	CUSHION		
45	1B		G11-1321-14	CUSHION		

E1: Scandinavia K: USA P: Canada E: Europe

Y: PX(Far East, Hawaii) T: England M: Other Areas

Y: AAFES(Europe) X: Australia

△ indicates safety critical components.

L-1000D L-1000D

PARTS LIST

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕 向	Re- marks 備考
46	3A, 3B	*	G11-1322-14	CUSHION		
47	1B	*	G11-2012-04	CUSHION		
48	2A, 2B	*	G11-2025-04	CUSHION		
49	2B	*	G11-2028-04	SOFT TAPE		
50	1A	*	G16-0741-04	SHEET		
57	1A		J11-0137-03	CLAMPER		
58	2B		J19-0516-05	UNIT HOLDER		
59	3B		J19-2874-04	HOLDER		
60	2A		J19-3119-04	HOLDER		
61	2B	*	J25-6316-15	FLEXIBLE ASSY		
62	2A, 2B		J42-0165-04	BUSHING		
63	2A, 2B	*	J42-0179-04	BUSHING		
64	2A		J90-0619-14	GUIDE		
65	1B, 2B		J90-0620-14	GUIDE		
66	1A	*	J99-0057-01	TRAY		
67	1A	*	J99-0072-04	TRAY ASSY		
-			J61-0019-05	WIRE BAND		
-			J61-0307-05	WIRE BAND		
70	2A		L90-0019-08	COIL		
71	3B		L90-0020-08	COIL		
75	3B		N19-0143-04	FLAT WASHER		
76	3B		N19-0891-04	FLAT WASHER		
77	2A, 2B		N19-0921-04	FLAT WASHER		
78	1A		N19-0945-04	FLAT WASHER		
79	1B, 2B		N19-1211-04	FLAT WASHER		
80	2B		N19-1212-04	FLAT WASHER		
A			N09-2664-05	STEPPED SCREW		
A		*	N30-2004-46	PAN HEAD MACHINE SCREW		
B		*	N09-2714-05	STEPPED SCREW		
B			N35-2008-46	BINDING HEAD MACHINE SCREW		
C			N39-2025-46	PAN HEAD MACHINE SCREW		
M			N32-2608-46	FLAT HEAD MACHINE SCREW		
N			N09-2801-05	MACHINE SCREW		
N			N35-2605-45	BINDING HEAD MACHINE SCREW		
P			N30-3003-46	PAN HEAD MACHINE SCREW		
Q			N84-3004-46	PAN HEAD TAPTITE SCREW		
R		*	N09-2593-05	TAPTITE SCREW		
R		*	N35-2605-46	BINDING SCREW		
S		*	N09-2591-05	TAPTITE SCREW		
S			N89-3006-46	BINDING HEAD TAPTITE SCREW		
T			N89-2604-45	BINDING HEAD TAPTITE SCREW		
U			N09-2675-05	TAPTITE SCREW		
U			N89-2606-46	BINDING HEAD TAPTITE SCREW		
V			N29-0067-05	PUSH RIVET (3.5X4.5)		
V			N89-2608-45	BINDING HEAD TAPTITE SCREW		
R1			RS14KB3A470J	PL-PROOF RS 47 J 1W		
S1 -4	1B, 2B		S33-1017-05	LEVER SWITCH		
85	1A		T50-1041-04	YÖKE		
86	2A	*	T50-1049-15	YÖKE ASSY		
87	3B	*	T50-1050-15	YÖKE ASSY		
88	1A		T99-0222-05	MAGNET		
CLM	1B		T42-0463-04	MOTOR ASSY (CLAMP)		

E1: Scandinavia K: USA P: Canada E: Europe

V: PX(Far East, Hawaii) T: England M: Other Areas

Y: AAFES(Europe) X: Australia

△ indicates safety critical components.

PARTS LIST / SPECIFICATIONS

* New Parts

Parts without Parts No. are not supplied.

Les articles non mentionnés dans le Parts No. ne sont pas fournis.

Teile ohne Parts No. werden nicht geliefert.

Ref. No. 参照番号	Address 位置	New Parts 新	Parts No. 部品番号	Description 部品名 / 規格	Desti- nation 仕 向	Re- marks 備考
DM	3A		T42-0499-14	MOTOR ASSY (DISC)		
LM	1B		T42-0498-04	MOTOR ASSY (LOADING)		
PU	3B		J91-0347-05	PICKUP		

E1: Scandinavia K: USA P: Canada E: Europe

Y: PX(Far East, Hawaii) T: England M: Other Areas

Y: AAFES(Europe) X: Australia

△ indicates safety critical components

Specifications

[Audio]

	BALANCED	UNBALANCED
Frequency response	2 Hz ~ 20 kHz, ± 0.2 dB	2 Hz ~ 20 kHz, ± 0.2 dB
Signal-to-noise ratio	more than 107 dB	more than 107 dB
Total harmonic distortion	0.0015% at 1 kHz	0.0015% at 1 kHz
Output ANALOG	4.0 V	2.0 V

Output

DIGITAL (COAXIAL) 0.5 V p-p, 75 Ω
(OPTICAL) -15 dBm ~ -21 dBm

Channel separation more than 108 dB at 1 kHz

Wow & flutter Below measurable limit

[General]

Power consumption 40 W

Dimensions W: 440 mm (17-5/16")

H: 131 mm (5-3/16")

D: 387 mm (15-1/4")

Weight 14 kg (30.8 lb)

[Format]

Type Compact disc player

Read system Non-contact optical pickup

Rotational speed About 200 to 500 rpm

Output connector CANNON connector

Note:

KENWOOD follows a policy of continuous advancements in development. For this reason specifications may be changed without notice.

Note:

Component and circuitry are subject to modification to insure best operation under differing local conditions. This manual is based on, the U.S.A. (K) standard, and provides information on regional circuit modification through use of alternate schematic diagrams, and information on regional component variations through use of parts list.

KENWOOD CORPORATION

Shionogi Shibuya Building, 17-5, 2-chome Shibuya, Shibuya-ku, Tokyo 150, Japan

KENWOOD U.S.A. CORPORATION

2201 East Dominguez Street, Long Beach, CA 90810;

550 Clark Drive, Mount Olive, NJ 07828, U.S.A.

KENWOOD ELECTRONICS CANADA INC.

P.O. BOX 1075, 959 Gene Court, Mississauga, Ontario, Canada L4T 4C2

TRIO-KENWOOD U.K. LTD.

KENWOOD HOUSE, Dwight Road, Watford, Herts., WD1 8EB United Kingdom

KENWOOD ELECTRONICS BENELUX N.V.

Mechelsesteenweg 418 B-1890 Zaventem, Belgium

KENWOOD ELECTRONICS DEUTSCHLAND GMBH

Rembrücken-Str. 15, 60506 Heusenstamm, West Germany

TRIO-KENWOOD FRANCE S.A.

13 Boulevard Ney, 75018 Paris, France

KENWOOD LINEAR S.p.A.

20125, MILANO-VIA ARBE, 90, ITALY

KENWOOD ELECTRONICS AUSTRALIA PTY. LTD. (INCORPORATED IN N.S.W.)

4E Woodcock Place, Lane Cove, N.S.W. 2066, Australia

KENWOOD & LEE ELECTRONICS, LTD.

Wang Kee Building, 4th Floor, 34-37, Connaught Road, Central Hong Kong

Accessories

- Audio cord 1
- CANNON cable 2



E30-2600-05



E31-2621-05 (BLUE)
E31-2622-05 (RED)

- Remote control unit 1
- Battery 2

- ("AA" or "R6")



(A70-0315-05)

